


Popular Trailer Connector Wiring Diagrams


6 PIN SOCKET



TM Tail Lights
GD Ground
LT Left/Stop
RT Right/Stop
S Brakes
A Auxiliary


Note: S & A are sometimes reversed
(horse trailers especially)

7 RV SOCKET




1 Ground
2 Electric Brakes
3 Tail Lights
4 Battery Charge
5 Left/Stop
6 Right/Stop
7 Auxiliary

9 RV SOCKET



1 Ground
2 Electric Brakes
3 Tail Lights
4 Battery Charge
5 Left/Stop
6 Right/Stop
7 Extra Auxiliary
8 Auxiliary
9 Reefer (tag) or Stop

4 PIN FLAT




1 Ground
2 Tail Lights
3 Left/Stop
4 Right/Stop

Carson Truck
& Auto Repair

775-883-7770

www.ctar.us

SEMI SOCKET



1 Ground
2 Clearance Lights
3 Left
4 Stop
5 Right
6 Tail
7 Auxiliary

Common wire color codes are: White = Ground, Black = Power, Red = Aux, Blue = Elec Brakes, Green = Right Turn, Yellow = Right Turn, Brown = Clearance